



Gehäuse Typen	M	L	K	N	P	Q	R ₁	R ₂	R ₃	R ₄	T
X80F	222	162	140	90,5	156	82,5	110	192	120	15	M 12 x 20
X110F	285	203	180	103	205	108	148	253	159	16	M 12 x 22
X140F	356	254	216	127	248	133,5	186	286	184	35	M 16 x 30
X180F	455	303	270	160	328	171,5	210	385	215	35	M 16 x 40
Toleranz				±0,5		±0,5					

Gehäuse Typen	Antriebswelle					Ausgangswelle				
	d	w	u	b	t	d ₁	w ₁	u ₁	b ₁	t ₁
TX 80F	20	52	50	6	3,5	30	60	60	8	4
TX110F	30	82	80	8	4	35	80	80	10	5
TX140F	35	82	80	10	5	45	112	110	14	5,5
TX180F	42	112	110	12	5	55	110	110	16	6
Toleranz	j ₆			P ₉		j ₆		j ₆	P ₉	